



# DATA SHEET

## Hall Effect Current Sensor

PN: CHB\_AP9S50/100/125

IPN=50~200A

### Feature

- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC, pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC +9~15 V
- PCB mounting installation

### Advantages

- High accuracy
- Easy installation
- Low temperature drift
- Optimized response time, no insertion losses
- Low power consumption
- High immunity to external interference
- Very good linearity
- Can be customized

### Applications

- The application of induction cooker
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS



### Electrical data: (Ta=25°C, Vc=+9.0VDC)

Parameter \ Ref	CHB50 AP9S50	CHB100 AP9S50	CHB125 AP9S125	CHB200 AP9S100
Rated input I <sub>pn</sub> (A)	50	100	125	200
Measuring range I <sub>p</sub> (A)	0~+150	0~+300	0~+375	0~+600
Turns ratio N <sub>p</sub> /N <sub>s</sub> (T)	1:1000	1:2000	1:1000	1:2000
Output current rms I <sub>S</sub> (mA)	+50*IP/IPN	+50*IP/IPN	+125*IP/IPN	+100*IP/IPN
Secondary coil resistance R <sub>S</sub> (Ω)	30	50	30	50
Inside resistance R <sub>M</sub> (Ω)	[(V <sub>C</sub> -0.6V)/ ( I <sub>S</sub> *0.001)]-R <sub>S</sub>			
Supply voltage V <sub>C</sub> (V)	(+9 ~ +15.0) ±5%			
Accuracy X <sub>G</sub> (%)	@IPN, T=25°C		< ±0.5	
Offset current I <sub>OE</sub> (mA)	@IP=0, T=25°C		< +0.2	
Temperature variation of IOE I <sub>OT</sub> (mA/°C)	@IP=0, -40 ~ +85°C		< ±0.005	
Linearity error ε <sub>r</sub> (%FS)			< 0.1	
Di/dt accurately followed (A/μs)			> 100	
Response time τ <sub>ra</sub> (μs)	@90% of IPN		< 1.0	
Power consumption I <sub>C</sub> (mA)			15+I <sub>s</sub>	
Bandwidth BW(KHZ)	@IPN		DC-DC	



Cheemi Technology Co., Ltd

Tel: 025-85996365

E-mail: info@cheemi-tech.com

www.cheemi-tech.com

Add: N22, Xianlongwan, Xianyin South Road, Qixia District, Nanjing - China.

Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	3.0
---------------------------	-------------------	-----

## General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55~ +125
Mass M(g)	21
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

## Dimensions(mm):

CHB_AP9S50/100	CHB125AP9S125	Connection
		<p>General tolerance</p> <p>General tolerance: &lt;math&gt;\pm 0.5\text{mm}&lt;/math&gt;            Primary through-hole : <math>10.5 \times 16.2 \pm 0.15\text{mm}</math>            Secondary pin: 3pin <math>0.6 \times 0.65</math></p>

## Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be  $< 100^\circ\text{C}</math>.$

**WARNING : Incorrect wiring may cause damage to the sensor.**

