



DATA SHEET

Hall Effect Current Sensor

PN: CHK_FDA24S0/4

IPN=50-600A

Feature

- Open- loop current transducer using the hall effect
- Capable measurement of currents: DC, AC,pulse with galvanic isolation betweenXXD primary circuit and secondary circuit.
- Output signal can be directly acquisition-ed by the PLC or DSP terminal control system.
- Supply voltage: DC +12.0~24.0V

Advantages

- Easy installation
- No insertion losses
- Low power consumption
- Wide current measuring range
- High immunity to external interference
- Can be customized

Applications

- The application of variable frequency electrical appliances
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS



Electrical data: (Ta=25°C, Vc=+24.0VDC)

Parameter	Ref	CHK50 FDA24S4	CHK100 FDA24S4	CHK200 FDA24S4	CHK300F DA24S4	CHK500F DA24S4	CHK600 FDA24S4
Rated input Ipn(A)		50	100	200	300	500	600
Measuring range Ip(A)		0 ~ +100	0 ~ +200	0 ~ +400	0 ~ +600	0 ~ +1000	0 ~ +1200
Output current Io(mA)		@CHK-FDA24S4 4.0+16.0*(IP/IPN),DC					
Output current Io(mA)		@IP=0,CHK-FDA24S4 4.0±0.15,DC					
Output current Io(mA)		@CHK-FDA24S0 +20.0*(IP/IPN),DC					
Offset current IOE(mA)		@IP=0,CHK-FDA24S0 < +0.2					
Supply voltage VC(V)		(+12.0~+24.0) ±5%					
Accuracy XG(%)		@IPN,T=25°C < ±1.0					
Temperature variation of IOE IOT(mA/°C)		@IP=0,-40 ~ +85°C < ±0.075					
Linearity error er(%FS)		< 1.0					
Response time tra(ms)		@90% of IPN <20					
Power consumption IC(mA)		15+IO					



Cheemi Technology Co., Ltd

Bandwidth Bw(KHZ)	@-3dB,IPN	DC-2.0
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	2.5

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55 ~ +125
Mass M(g)	240
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

Connection

General tolerance

General tolerance: $\pm 0.5\text{mm}$
 Primary through-hole : $12.5 \times 41 \pm 0.3$
 Connection of Secondary :
 2510-04A (Instead of Molex 5045-04A)

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^{\circ}\text{C}</math>.

WARNING : Incorrect wiring may cause damage to the sensor.

