



# DATA SHEET

## Hall Effect Voltage Sensor

PN: CHV\_AS5S6

IPN=05/10mA

### Feature


- Closed- loop (compensated) voltage transducer
- Capable measurement of DC and AC voltage with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC +5.0V

### Advantages

- High accuracy
- Easy installation
- Low temperature drift
- High immunity to external interference
- Very good linearity
- Can be customized

### Applications

- The application of induction cooker
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)



RoHS



### Electrical data: (Ta=25°C, Vc= +5.0VDC, RL=2KΩ)

Parmeter	Ref	CHV05AS5S6	CHV10AS5S6
Rated input Ipn(mA)		05	10
Measuring range Ip(mA)		0 ~ ±10	0 ~ ±20
Rated input voltage VP(N)V		5 ~ ±1200	10 ~ ±500
Turns ratio Np/NS (T)		2500:1000	1250:1000
Primary coil resistance RP (Ω)		170	80
Secondary coil resistance RS (Ω)		60	60
Inside resistance RM (Ω)		50±0.1%	50±0.1%
Output voltage VO(V)		2.500±0.625*(IP/IPN)	
Output voltage VO(V)	@IP=0,T=25°C	2.500	
Supply voltage VC(V)		+5.0 ±5%	
Accuracy XG(%)	@IPN,T=25°C	< ±0.5	
Offset voltage VOE(mV)	@IP=0,T=25°C	< ±20	
Temperature variation of VOE VOT(mV/°C)	@IP=0,-40 ~ +85°C	< ±1.0	
Linearity error er(%FS)		< 0.1	
Response time tra(μs)	@90% of IPN	<40.0	
Power consumption IC(mA)		15+Is	
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	2.5	



## General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55~ +125
Mass M(g)	22
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

## Dimensions(mm):

	<p><b>Connection</b></p>
	<p><b>General tolerance</b></p> <p>General tolerance: &lt;math&gt;\pm 0.2\text{mm}&lt;/math&gt;  size of Primary pin :  2pin, <math>0.8*0.8 \pm 0.15\text{mm}</math> ;  Secondary 4pin: <math>0.65*0.65 \pm 0.15\text{mm}</math></p>

### Instruction for use of the voltage sensor model CHV10AS5S6:

- ◆ Primary resistance R1: the sensor's optimum accuracy is obtained at the rated current. So R1 should be calculated so that the rated voltage to be measured corresponds to a primary current of 10mA.
  - ◆ For example: Measuring rated voltage  $VPN=250V$ :
    - a)  $R1=25K/2.5W, IP=10mA$  Accuracy= $\pm 0.5\%$  of  $VPN$ ; b)  $R1=50K/1.25W, IP=05mA$  Accuracy= $\pm 1.0\%$  of  $VPN$ ;
- Operating range(recommended):taking into the resistance of the primary windings(which must remain low compared to R1.in order to keep thermal deviation as low as possible) and the isolation,the sensor is suitable for measuring nominal voltage from 10 to 500V.

## Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.

**WARNING : Incorrect wiring may cause damage to the sensor.**

