



# DATA SHEET

## Hall Effect Current Sensor

**PN: CHK\_EKBD24S5**

**IPN=200-2000A**

### Feature

- Open-loop current transducer using the hall effect
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Output signal can be directly acquisition-ed by the PLC or DSP terminal control system.

### Advantages

- Easy installation
- No insertion losses
- Low power consumption
- Wide current measuring range
- High immunity to external interference

### Applications

- The application of variable frequency electrical appliances
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



### Electrical data: (Ta=25°C , Ve=+24.0VDC)

Parameter \ Ref	CHK200E KBD24S5	CHK400E KBD24S5	CHK800E KBD24S5	CHK1000 EKBD24S 5	CHK1500 EKBD24S 5	CHK2000 EKBD24S 5
Rated input Ip(A)	200	400	800	1000	1500	2000
Measuring range Ip(A)	0 ~ +400	0 ~ +800	0 ~ +1600	0 ~ +2000	0 ~ +3000	0 ~ +4000
Output voltage DC Vo(V)	$\pm 5.0^*(IP/IPN)$ , DC					
Load resistance RL(KΩ)	>10					
Offset voltage VOE(mV)	<+40					
Supply voltage VC(V)	(+12.0~+24.0) ±5%					
Accuracy XG(%)	@IPN,T=25°C      <±1.0					
Temperature variation of VOE VOT(mV/°C)	@IP=0,-40 ~ +85°C      <±1.0					
Hysteresis offset voltage VOH(mV)	@IP=0,after 1*IPN      <+20					
Linearity error er(%FS)	< 1.0					
Response time tra(ms)	@90% of IPN      <20					
Power consumption IC(mA)	15+IO					



# Cheemi Technology Co., Ltd

Bandwidth Bw(KHZ)	@-3dB,IPN	DC-2.0
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	2.5

## General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C )	-55~ +125
Mass M(g )	120
Plastic material	PBT G30/G15, UL94- VO;
Standards	IEC60950-1:2001 EN50178:1998 SJ20790-2000

## Dimensions(mm):

CHK-EKBD24S4M	CHK-EKBD24S4S	Connection	
		General tolerance	
General tolerance:< ±0.5mm			
Primary through-hole : D40.5±0.3			
Connection of Secondary :			
CHK-EKBD24S4M: 2510-04A (Instead of Molex 5045-04A) CHK-EKBD24S4S: 15EDGK3.81-04P			

## Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole if fully filled with.
- The primary conductor should be <100°C.

**WARNING : Incorrect wiring may cause damage to the sensor.**

