



DATA SHEET

Hall Effect Current Sensor

PN: CHB_LSP3S1H

IPN=10~40A

Feature

- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC +3.3/5.0V
- PCB mounting installation

Advantages

- High accuracy
- Low temperature drift
- Optimized response time, no insertion losses
- Low power consumption
- Very good linearity
- Can be customized

Applications

- Photovoltaic (PV) current applications
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS

Electrical data: (Ta=25°C, Vc=+3.3/5.0VDC,RL=2KΩ,CL=10000pF)

Ref Parmeter	CHB10LSP3S1H	CHB15LSP3S1H	CH20LSP3S1H	CHB40LSP3S1H
Rated input Ipn(A)	10	15	20	40
Measuring range Ip(A)	0~±10	0~±15	0~±20	0~±40
Turns ratio Np/NS (T)	1:1000	1:1200	1:800	1:800
Inside resistance RM(Ω)	31.25±0.1%	24.9±0.1%	12.5±0.1%	6.25±0.1%
Output voltage Vo(V)	1.650±1.250*(IP/IPN)			
Output voltage Vo(V)	@IP=0,T=25°C		1.650	
Supply voltage VC(V)	+3.3~+5.0 ±5%			
Accuracy XG(%)	@IPN,T=25°C		< ±0.5	
Offset voltage VOE(mV)	@IP=0,T=25°C		< ±10	
Temperature variation of VOE VOT(mV/°C)	@IP=0,-40 ~ +85°C		< ±0.05	
Linearity error er(%FS)	< 0.1			
Di/dt accurately followed (A/μs)	> 50			
Response time tra(μs)	@90% of IPN		< 1.0	



Cheemi Technology Co., Ltd

Tel: 025-85996365

E-mail: info@cheemi-tech.com

www.cheemi-tech.com

Add:N22, Xianlongwan, Xianyin South Road, Qixia District, Nanjing - China.

Power consumption IC(mA)		10+Is
Bandwidth BW(KHZ)	@-3dB,IPN	DC-200
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	4.0

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55 ~ +125
Mass M(g)	10
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

	Connection
	General tolerance
	<p>General tolerance: <math>\pm 0.2\text{mm}</math> Primary through-hole: <math>D8.5 \pm 0.15\text{mm}</math> Fixed pin: <math>0.8 * 0.9 \pm 0.15\text{mm}</math>; Secondary pin: 3pin <math>0.25 * 0.5</math></p>

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^{\circ}\text{C}</math>.

WARNING : Incorrect wiring may cause damage to the sensor.

